

Specifications:

LED: Samsung / Philips mid power LED
CRI: Min 80
Body: Steel
Diffuser: Acrylic
Finish: See options
Driver: Standard 0-10v dimming
Mounting: Directly to standard J-box
Warranty: 5 year on LED module/driver
Listing : Damp location



Decorative pendant utilizing LED technology. Available in five sizes and several LED packages. Flat trim ring and 3-rod pendant stem available in choice of finishes. Suitable for a variety of application: dining rooms, board rooms, reception areas and more

LED information:

Size	Lumens Up/Down	Wattage Up/Down
24"	1096L/4800L	9.1/28.3
24"	1641L/5800L	13.3/36.6
30"	1641L/5800L	13.3/36.6
30"	1641L/6600L	13.3/42.5
36"	1641L/8800L	13.3/54.6
36"	2781L/10000L	21.9/66.1
42"	2781L/10000L	21.9/66.1
42"	2781L/14000L	21.9/82.0

Dimensions:

Model	Dia	Bowl Depth	OAH*
LPM3224	24"	6"	42"
LPM3230	30"	6"	42"
LPM3236	36"	6"	42"
LPM3242	42"	6"	42"
LPM3248	48"	6"	42"

*height customizable



ORDERING INFORMATION

Example: LPM3230-1641L/5800L-40K-WA-CORB-OAH48

MODEL #	LED MODULE	KELVIN	OPTIONS	VOLTAGE
LPM3224	1096L/4800L-1096L/4800L; 9.1/28.3w	30K – 3000K	DIFFUSER	UNV– 120/277Vv 0-10v dimming
	1641L/5800L-1641L/5800L; 13.3/36.6w	35K – 3500K	WA – white acrylic	347 – 347v 0-10v dimming
		40K – 4000K	WFA – white faux alabaster	TRIAC – consult
LPM3230	1641L/5800L-1641L/5800L; 13.3/36.6w	50K – 5000K	WSA – white sanded acrylic	
	1641L/6600L-1641L/6600L; 13.3/42.5w		FINISH-cured	
			CAB – cured antique brass	
LPM3236	1641L/8800L-1641L/8800L; 13.3/54.6w		CBN – cured brushed nickel	
	2781L/10000L-2781L/10000L; 21.9/66.1w		CCH – cured chrome	
			CORB – cured oil rubbed bronze	
LPM3242	2781L/10000L-2781L/10000L; 21.9/66.1w		CPB – cured polished brass	
	2781L/14000L-2781L/14000L; 21.9/82.0w		FINISH-plated	
			ABP – plated antique brass	
			BNP – plated brushed nickel	PENDANT
			CHP – plated chrome	OAHxx – overall height
			ORBP – plated oil rubbed bronze	
			PBP – plated polished brass	

*uplight subject to change based on overall height



www.ovallighting.com

Job Name			
Type			
Part #			
Lamping		Voltage	